

LED RGB Remote Controller & Dimmer

Working Temp: -20 - 60 Celcius

External Dimensions: 121mm X 75mm X 25mm

Connecting Code: Common Anode

Supply Voltage: DC 12V

Output: Three Channels

AUDIO



Control Mode:

(ON/OFF) - Operation to turn ON and OFF controller at any time

(PAUSE) - When you want to see a static effect of LED, you may press this button to pause

(S+) - The speed changing progression will increase every time the button is pressed (100 Steps)

(S-) - The speed changing progression will decrease every time the button is pressed

(B+) - Adjusting brightness button, will increase every time the button is pressed (255 Steps)

(B-) - Adjusting brightness button, will decrease every time the button is pressed

(M+) - Pattern function key, up direction, there are 22 pre-set programs in all

(M-) - Pattern functionkey, down direction

Items	Patterns	Remarks
1	Static RED	Brightness is Adjustable, Speed is Nonadjustable
2	Static BLUE	
3	Static PURPLE	
4	Static GREEN	
5	Static YELLOW	
6	Static CYAN	
7	Static WHITE	
8	3 color jumpy changing	Speed and brightness are Adjustable
9	7 colot jumpy changing	
10	3 color gradual changing	Speed is Adjustable, Brightness is Nonadjustable
11	7 color gradual changing	
12	RED Flash	Speed and brightness are Adjustable
13	BLUE Flash	
14	PURPLE Flash	
15	GREEN Flash	
16	YELLOW Flash	
17	CYAN Flash	
18	WHITE Flash	
19	Red/Blue crossfade	Speed is Adjustable, Brightness is Nonadjustable
20	Blue/Green crossfade	
21	Green/Red crossfade	
22	Audio Pattern	

8 Key Controller

